

An exact solution to the Dirac equation for a time dependent Hamiltonian in 1-1D space-time.

Dan Solomon
Rauland-Borg Corporation

Email: dan.solomon@rauland.com
May 30, 2009

Abstract.

We find an exact solution to the Dirac equation in 1-1 dimension space-time in the presence of a time-dependent potential which consists of a combination of electric, scalar, and pseudoscalar terms.

1. Introduction.

In this paper we find an exact solution to the Dirac equation in 1-1 dimensional space-time in the presence of a time-dependent potential which consists of a combination of electric, scalar, and pseudoscalar terms. In the following discussion we set $\hbar = c = 1$ and let x and t stand the space and time dimensions, respectively. In this case the Dirac equation for a single electron in the presence of an external potential $v(x, t)$ is,

$$i \frac{\partial \psi(x, t)}{\partial t} = (H_0 + v(x, t)) \psi(x, t) \quad (1.1)$$

where,

$$H_0 = \left(-i\sigma_1 \frac{\partial}{\partial x} + m\sigma_3 \right) \quad (1.2)$$

and where σ_j ($j = 1, 2, 3$) are the Pauli matrices. In the above $v(x, t)$ must be hermitian.

As noted in [1] most general form for $v(x, t)$ is,

$$v(x, t) = V_t(x, t) + \sigma_3 V_s(x, t) + \sigma_1 V_e(x, t) + \sigma_2 V_p(x, t) \quad (1.3)$$

In this expression V_t and V_e stands for the time and space components, respectively, of the 2-vector potential, V_s stands for the scalar term, and V_p is the pseudoscalar term. As discussed in [1], the term $V_e(x, t)$ can always be set equal to zero by a gauge transformation. So in the following discussion we set $V_e(x, t) = 0$. Therefore, using the above, the Dirac equation (1.1) can be written as,

$$i \frac{\partial \psi(x, t)}{\partial t} = (H_0 + V_t(x, t) + \sigma_3 V_s(x, t) + \sigma_2 V_p(x, t)) \psi(x, t) \quad (1.4)$$

Some examples of solutions of the Dirac equation in the presence of a static pseudopotential are given in Ref. [1] – [4].

2. Time dependent potentials.

Let the potential terms satisfy the following relationships,

$$V_s(x, t) = m(\cos(2g(x, t)) - 1) \quad (2.1)$$

$$V_p(x, t) = -m \sin(2g(x, t)) \quad (2.2)$$

$$V_t(x,t) = \frac{\partial f(x,t)}{\partial t} + \frac{\partial g(x,t)}{\partial x} \quad (2.3)$$

In the above expressions $g(x,t)$ is an arbitrary function and $f(x,t)$ satisfies,

$$\frac{\partial f(x,t)}{\partial x} = -\frac{\partial g(x,t)}{\partial t} \quad (2.4)$$

Given the above relationships it will be shown that the solution to the Dirac equation (1.4) can be written as,

$$\psi(x,t) = e^{-if(x,t)} e^{-i\sigma_1 g(x,t)} \psi_0(x,t) \quad (2.5)$$

where $\psi_0(x,t)$ is the solution to the free field Dirac equation, i.e.,

$$i \frac{\partial \psi_0(x,t)}{\partial t} = H_0 \psi_0(x,t) \quad (2.6)$$

Solutions to this free field equation in 1-1 dimensional space-time are given in [5] (See Eq. 2.4 of [5]).

Define $U = e^{-if(x,t)} e^{-i\sigma_1 g(x,t)}$ so that $\psi(x,t) = U \psi_0(x,t)$. To prove that (2.5) is a solution to (1.4), given (2.1) - (2.4), we will substitute $\psi(x,t) = U \psi_0(x,t)$ into both sides of (1.4) and show that the equality still holds. This yields,

$$i \left(\frac{\partial U}{\partial t} \right) \psi_0 + iU \left(\frac{\partial \psi_0}{\partial t} \right) = (H_0 + V_t + \sigma_3 V_s + \sigma_2 V_p) U \psi_0 \quad (2.7)$$

Multiply both sides by $U^{-1} = e^{+i\sigma_1 g(x,t)} e^{+if(x,t)}$ to obtain,

$$iU^{-1} \left(\frac{\partial U}{\partial t} \right) \psi_0 + i \left(\frac{\partial \psi_0}{\partial t} \right) = U^{-1} (H_0 + V_t + \sigma_3 V_s + \sigma_2 V_p) U \psi_0 \quad (2.8)$$

The Pauli matrices satisfy $\{\sigma_i, \sigma_j\} = 2\delta_{ij}$. Using this we obtain the following useful relationships,

$$[U, \sigma_1] = [U^{-1}, \sigma_1] = 0; \quad e^{i\sigma_1 g(x,t)} \sigma_3 = \sigma_3 e^{-i\sigma_1 g(x,t)}; \quad e^{i\sigma_1 g(x,t)} \sigma_2 = \sigma_2 e^{-i\sigma_1 g(x,t)} \quad (2.9)$$

From this we obtain,

$$U^{-1} \sigma_3 U = e^{i\sigma_1 g(x,t)} \sigma_3 e^{-i\sigma_1 g(x,t)} = \sigma_3 e^{-i\sigma_1 2g(x,t)} \quad (2.10)$$

and

$$U^{-1} \sigma_2 U = e^{i\sigma_1 g(x,t)} \sigma_2 e^{-i\sigma_1 g(x,t)} = \sigma_2 e^{-i\sigma_1 2g(x,t)} \quad (2.11)$$

To evaluate (2.8) use,

$$U^{-1}H_0(U\psi_0) = \left(-i\sigma_1 U^{-1} \frac{\partial U}{\partial x} \psi_0 - i\sigma_1 \frac{\partial \psi_0}{\partial x} + mU^{-1}\sigma_3 U\psi_0 \right) \quad (2.12)$$

Next use,

$$U^{-1} \frac{\partial U}{\partial x} = -i \left(\frac{\partial f(x,t)}{\partial x} + \sigma_1 \frac{\partial g(x,t)}{\partial x} \right) \quad (2.13)$$

along with (2.10) and (2.11) in (2.12) to obtain,

$$U^{-1}H_0(U\psi_0) = - \left(\sigma_1 \frac{\partial f(x,t)}{\partial x} + \frac{\partial g(x,t)}{\partial x} \right) \psi_0 + H_0\psi_0 + m\sigma_3 (e^{-i\sigma_1 2g} - 1) \psi_0 \quad (2.14)$$

We also have that,

$$U^{-1} \left(\frac{\partial U}{\partial t} \right) = -i \left(\frac{\partial f(x,t)}{\partial t} + \sigma_1 \frac{\partial g(x,t)}{\partial t} \right) \quad (2.15)$$

Use this and (2.14) in (2.8) to obtain,

$$\begin{aligned} \left(\frac{\partial f}{\partial t} + \sigma_1 \frac{\partial g}{\partial t} \right) \psi_0 + i \left(\frac{\partial \psi_0}{\partial t} \right) &= - \left(\sigma_1 \frac{\partial f}{\partial x} + \frac{\partial g}{\partial x} \right) \psi_0 + H_0\psi_0 - m\sigma_3\psi_0 + V_t\psi_0 \\ &+ (m\sigma_3 + \sigma_3 V_s + \sigma_2 V_p) e^{-i\sigma_1 2g} \psi_0 \end{aligned} \quad (2.16)$$

Next, use (2.6) in the above to obtain,

$$\left(\frac{\partial f}{\partial t} + \sigma_1 \frac{\partial g}{\partial t} \right) \psi_0 = - \left(\sigma_1 \frac{\partial f}{\partial x} + \frac{\partial g}{\partial x} \right) \psi_0 - m\sigma_3\psi_0 + V_t\psi_0 + (m\sigma_3 + \sigma_3 V_s + \sigma_2 V_p) e^{-i\sigma_1 2g} \psi_0 \quad (2.17)$$

Rearrange terms to obtain,

$$\left(\frac{\partial f}{\partial t} + \sigma_1 \frac{\partial g}{\partial t} \right) + \left(\sigma_1 \frac{\partial f}{\partial x} + \frac{\partial g}{\partial x} \right) + m\sigma_3 - V_t = ((m + V_s)\sigma_3 + \sigma_2 V_p) e^{-i\sigma_1 2g} \quad (2.18)$$

Use (2.3) and (2.4) in the above to obtain,

$$m\sigma_3 e^{i\sigma_1 2g} = (m + V_s)\sigma_3 + \sigma_2 V_p \quad (2.19)$$

Use $\sigma_2 = i\sigma_1\sigma_3$ along with (2.1) and (2.2) in the above,

$$\sigma_3 e^{i\sigma_1 2g} = \sigma_3 \cos(2g) - i\sigma_1\sigma_3 \sin(2g) = \sigma_3 (\cos(2g) + i\sigma_1 \sin(2g)) \quad (2.20)$$

This equality holds because $e^{i\sigma_1 2g} = \cos(2g) + i\sigma_1 \sin(2g)$. Therefore it is proved that (2.5) is a solution of the Dirac equation (1.4) where the potential terms are given by equation (2.1) - (2.4).

Another result that follows is that we can easily obtain exact solutions for the time-independent Hamiltonian which is obtained by making g time independent, i.e., setting $g(x, t) = g(x)$ in Eqs. (2.1) - (2.3) where as shown by (2.4) $f(x, t) = 0$. In this case the solution to the Dirac equation is $\psi(x, t) = e^{-i\sigma_1 g(x)} \psi_0(x, t)$.

References.

1. A. S. de Castro, "Bound state by a pseudoscalar coulomb potential in one-plus-one dimensions." Phys. Lett. A318 (2003) 40-47. See also arXiv:hep-th/0303175.
2. A. S. de Castro, "Scattering of neutral fermions by a pseudoscalar potential step in two-dimensional space-time." Phys. Lett A309(2003) 340-344. See also arXiv:hep-th/0302042v1.
3. A. S. de Castro, "Confinement of neutral fermions by a pseudoscalar double-step potential in (1+1) dimensions." Phys. Lett A308(2003) 131-134. See also arXiv:hep-th/0301053v1.
4. F.M. Toyama and Y. Nogami. "Harmonic oscillators in relativistic quantum mechanics." Physical Review A. Vol 59, No. 2 (1999) 1056-1062.
5. D. Solomon, "Some new results concerning the vacuum in Dirac Hole Theory", Phys. Scr. 74(2006) 117-122. See also arXiv:quant-ph/0607037.